





















Exchangeable Tips for Ewent Laptop AC Adapter

Standard Tips EW3984 and EW3985 and EW3986

Type	Picture	Output Voltage	Tips Size	Included in	Suitable for notebook brands	Fit for laptops
A		19.0V - 2.1A	φ2.5*0.7		Asus	ASUS: Eee PC 1005HA, 1008HA, 1101HA, 1104HA, 1106H ASUS : ADP-40PH AB EeePC X101CH, S101H,T101H, 1011CX/PX, 1015BX/CX/E/B/PX/PW/PEM/PED/PT/T/PE, 1025C/CE, R025C, 1225B, 1215P/B/N-3/T, 1201N/NL/K/HA/T/PN/HAP, VX6S
B		19.0V - 2.37A 3.42A 4.74A	φ5.5*1.7	EW3984 EW3985 EW3986	Acer	Acer: See full details list
C		19.0V 1.58A 2.37A 3.42A 4.74A	φ4.0*1.7		HP	HP: See full details list
D		19.5V - 2.37A 3.42A 4.74A	φ5.0*3.0		Samsung	Samsung: X / M / P / Q / R / V / V M / GT series Samsung Notebook R428 R410 R65 R520 R522 R530 R580 R560 R518 R410 R429 Samsung Q468 Q230 Q208 QX310 Q310 Q320 Q210
E		19.5V - 3.33A 4.62A	φ4.5*3.0	EW3984 EW3985 EW3986	HP	HP Envy: 19.5V 3.33A,19.5V 4.62A HP Pavilion 14-n030TX NB PC, 14-n031TX NB PC, 14-n221TU NB PC, 14-n232TU NB PC, 14-n242TU TS NB PC, 14-n294TX NB PC, 14-n295TX NB PC, 14-n296TX NB PC, 100% Compatible with P/N: 714657-001, 714159-001, 710412-001, 709985-002 HP Envy Touchsmart Sleekbook 15 17 M6 M7 Series; HP Pavilion 11 14 15 17, HP Stream 11 13 14
F		19.0V - 2.37A 3.42A 4.74A	φ4.0*1.35	EW3984 EW3985 EW3986	Asus	ASUS : X553 X553M X553MA X553S X553SA Zenbook UX303UA UX303UB UX305CA UX305FA UX305LA UX305UA UX360CA ASUS : Flip Q302L Q302LA-BBI5T14 Q302LA-BBI5T19 Q302LA-BHI3T09 Q302LA-BHI3T11 Q302LA-BSI5T16. ASUS : Transformer Book Flip Trio T300 T300LA TP300 TP300LA TP300LD TX201 TX201LA T300LA-DH51T TP300LD-RHI5T15
G		20.0V - 3.25A 4.5A	φ7.9*5.5		IBM Lenovo	LENOVO: 3000 Series: C100, CZ00, N100, N200, V100, VZ00; Z Series: Z60m, Z60t, Z61e, Z61m, Z61p, Z61t; IBM ThinkPad X Series: X60, X60s, X61, X60 Tablet; ThinkPad T Series: T60, T60p, T61, T61p T400 T500; ThinkPad R Series: R60. R60e. R60i, R61. R61e, R61
H		18.5V 3.5A	φ7.45*5.0		HP / Compaq	HP Compaq Business notebooks: nc2400, nc2400, nc4200, nc4400, nc6220, nc6230, nc6320, nc6400, nx6310, nx6315, nx6320, nx6325, nx7300, nx7400, 2210, 2210b, 2510, 2510b, 2510p, 2710, 2710b, 6510b, 6515b, 6710b, 6715b, 6715s, 6720t, 6910b, 8510b, 8510w, 8710b, 8710w, TabletPC TC4400; HP Pavillion DV2, DV3, DV4, DV5, DV6, DV7 series , Compaq Presario CQ20, CQ40, CQ45, CQ50, CQ60, CQ70 series; HP G70 series; HP Ultrabook ENVY 13t Spectre series

J		18.5V 3.5A 4.86A	Φ4.8*1.7		HP / Compaq Asus	HP / Compaq: See full details list Asus: See full details list
K		18.5V 3.5A 4.86A	4.8*1.7	EW3984 EW3985 EW3986	HP/Compaq Delta Asus Nec	HP/COMPAQ, DELTA, ASUS, NEC
L		19.0V 2.37A 3.42A 4.74A	Φ 5.5*2.5	EW3984 EW3985 EW3986	IBM / LS / Dell / HP Delta / Toshiba Liteon / Gateway Nec	See full details list
M		19.5V 2.3A 3.33A 4.62A	Φ 6.0*4.3		Sony Fujitsu	SONY: VAIO PCG-505 series, VAIO PCG-V505R, VAIO PCG-VX series,VA10 PCG-GR series,VAIO PCG-SR series; VAIO PCG-SRX Series,VAIO PCG-Z1xx Series,VAIO VGN-TX, VAIO VGN-T, VAIO VGN-TZ, VAIO VGN-UX Series
N		19.0V 2.1A 2.36A 3.42A 4.74 A	Φ 3.0*1.1	EW3984 EW3985 EW3986	Samsung	See full details list
P		19.5V 2.31A 3.33A 4.62A	Φ 4.5*3.0		Dell Ultrabook	Dell: See full details list
Q		19.5V 2.31A 3.33A 4.62A	Φ 7.4*5.0	EW3984 EW3985 EW3986	Dell	See full details list
R		19.0V 2.37A 3.42A 4.74A	Φ 4.0*1.0		Asus	Asus: VivoBook X202 X201 K200CA C200 C300 C300MA X200 X200CA X200MA Q200 S200, Eee Book E402MA E403sa E502MA EXA1206UH
S		19.0V 2.37A 3.42A 4.74A	Φ 5.5*2.1		Acer	Acer: See full details list
T		19.5V 3.33A 4.62A	Φ 4.8*1.7		HP	HP Pavilion Chromebook 14, 14-b00, 14-c00; 15, 15-b00, 15-c00 Series; HP Envy Pro 4, 4t, 6, 6t, 6z, 13, 13t; HP Touchsmart Sleekbook 4, 6; HP Pavilion Sleekbook 6, 14-b, 14-c, 14-f, 14z-b, 14-b000, 14-c000,14-f000, 14z-b000, 15-b, 15t-b. 15z-b, 15-b000, 15z-b000 Series; HP Envy Spectre Xt Pro 13 14 15; HP Spectre XT Touchsmart 13, 14, 15, nv13, nv14, nv15;

U		20.0V 3.25A 4.5A	11*4.6	EW3984 EW3985 EW3986	Lenovo	Lenovo: See full details list
V		19.0V 2.1A 3.42A 4.74A	φ6.4*2.3		Asus	Asus Eeebook E202SA E205SA X205TA X205T X205 E200Ha TP200S T100HA; Asus vivobook E200 E200 E200H E200HA E202 E202S X205
W		19.0V 2.31A 3.42A 4.74A	φ4.5*3.0		Asus	Asus
Y		19.0V 1.58A 2.37A 3.42A 4.74A	φ4.0*1.7		HP	HP

Free Tip Service

If your laptop/notebook requires another tip then the tips which are supplied with this product, you can send a request for the right tip to Ewent (please check the tiplist in this manual). We cannot guarantee that we have the requested tip at all time. When available, our support desk will send the tip to you for free. If your laptop/notebook requires another tip then the tips which are supplied with this product, you can send a request for the right tip to Ewent (please check the tiplist in this manual). We cannot guarantee that we have the requested tip at all time. When available, our support desk will send the tip to you for free.

You can send your request for the tip to us by using the supportform on our website: <https://support.ewent-online.com/hc/nl/requests/new>