

DVI Single Link Video up to 1920 x 1200

QuickSwitch button for easy switching by a mere flip!

Switching Software Client for Windows & Mac included!!

Software hotkeys & Universal Hotkeys both available!!!

2 x USB 2.0 Hub Ports for keyboard, mouse or high-speed USB devices!!!!

UDV-TA2

2-port DVI USB Cable KVM Switch w/ Audio & Mic

1 x 1.5M Wired QuickSwitch button for instant desktop switching
2 x 0.9M fixed KVM & Audio/Mic Combo Cables (2 x USB)

The UDV-TA2 is a 2-port compact DVI USB “Cable KVM Switch” with 2 sets of fixed USB KVM & Audio/Mic combo cables and a wired QuickSwitch button for easy connection to your two computers. It allows you to access, control, boot and reboot two DVI and USB-enabled *multimedia* computers with only one USB keyboard, mouse, DVI display *and a speaker set and microphone*. For easy and fast switching between two computers, you can use either keyboard hotkeys, the QuickSwitch button or the Switching Software Client installed on your PCs!

QuickSwitch button for instant switching operation

The QuickSwitch button can be conveniently placed near your hand on the desktop. Whenever you need to switch computer channel, you can press it lightly for instant switching to the other computer. It is the most easy and fastest way to switch. The QuickSwitch button comes optionally either with a soft-magnet bottom to be readily attached to any metal surface, or with a Velcro sticker to be applied to any spot you like. Beside the QuickSwitch button, you can also use the keyboard hotkeys and software switching utility.

Switching Software Support for PC and Mac

The UDV-TA2 comes with both Windows and Mac version of the Switching Software utility program that can be installed on the connected computers to facilitate easy “software” switching. The Switching Software can show you the current active PC, and allows you to select PC as well as configure keyboard hotkeys. It appears as an icon on the system tray of your Window desktop, and will change its number icon upon switching to show the active computer port. With this software utility, it will give KVM users utmost convenience and control.



UDV-TA2 2-port Compact DVI USB Cable KVM Switch w/ Audio & Mic, QuickSwitch button

USB 2.0 hub ports compliant for USB keyboard, mouse and high-speed device sharing

The USB 2.0 interface offers multi-platform support for PC and Macintosh. The two USB 2.0 keyboard and mouse ports are actually transparent USB hub ports that feature a full driver support for advanced keyboard/mouse functionalities. In addition to the usual connections of a set of USB keyboard and mouse, the two USB 2.0 keyboard & mouse ports can also be connected to high-speed USB devices such as USB disk storage or webcam, etc.

DVI interface technology to ensure digitally crisp and clean imaging

The DVI interface technology is tailored to modern digital Flat Panel Display. It implements genuinely digital signal transmission over the cable to reduce undesired distortion from conventional analog/digital conversion. This DVI USB KVM Switch supports digital video (1920 x 1200) for your maximum convenience in adapting to your display requirements.

Audio and Microphone Switching offers uninterrupted multimedia experience

The audio and microphone switching function of UDV-TA2 allows you to leverage the multimedia systems on each of your two computers. You can monitor the audio/mic input/output of each computer without plugging on and off the audio/mic cables. User can also choose to use either independent/simultaneous switching of both PC channel and audio/microphone channel for their maximum convenience. And it takes only one set of speaker and microphone instead of one set for each computer. Furthermore, it offers you a user-programmable simultaneous/independent switching option between PC and audio/mic channel switching.

Zero Cabling Hassles for KVM users

This Cable KVM Switch saves you cabling troubles with its 2 x fixed KVM and audio/mic cables (USB + USB). In fact, you will have zero cabling troubles since you don't have to worry about finding suitable cables to fit--It's already fixed!

Features

- 2-port DVI USB Cable KVM Switch with 2 x *fixed* USB KVM & Audio/Mic Combo Cables
- 1 x fixed wired (1.5M) QuickSwitch button for instant toggling between two computers
- 2 x fixed (0.9M) DVI USB KVM audio/mic Combo cables
- Windows and Mac version of Switching Software Utility for easy switching
- USB 2.0 hub ports for keyboard, mouse or other high-speed USB devices
- DVI Single Link Digital Video up to 1920 x 1200 resolution
- Audio and Microphone switching for uninterrupted multimedia experience across multi-platforms
- Configurable independent/simultaneous switching of both PC and audio/mic channel
- Multi-platform support for PC and Macintosh platforms
- Hot-plugging PCs for maintenance without powering down the KVM Switch or PCs
- User definable hotkeys and universal hotkey for PC switching
- 3 modes of Channel selection – either by QuickSwitch button, keyboard hotkeys or Switching Software
- LED indicators for easy status monitoring
- USB interface power

Specifications

| Model No. | UDV-TA2 |
|-------------------------|---|
| PC Connections | 2 |
| Console Connections | 1 |
| Cables | Fixed 2 x USB DVI KVM & Audio/Mic Combo Cables |
| PC Port Connectors | 2 x USB Type A 2 x DVI-I 2 x 3.5mm audio plug 2 x 3.5mm mic plug |
| Console Port Connectors | 2 x USB 2.0 Type A (Keyboard & Mouse / High-speed USB devices) 1 x DVI 1 x 3.5mm audio jack 1 x 3.5mm mic jack |
| KVM Cables | 2 x fixed 0.9M DVI USB KVM & audio/mic combo cable |
| QuickSwitch button | 1 x 1.5M QuickSwitch Button for instant switching |
| PC selection | QuickSwitch button/Hotkeys/Switching Software |
| PC port LED | 2 x Green |
| Video resolution | DVI Single Link - 1920 x 1200 |
| Power Type | USB interface power |
| Size | Cable KVM |
| Dimensions (L x W x H) | 38 x 20 x 11mm |
| Housing | Plastic |
| Safety / Emission | FCC, CE |